

Application Note

AN-VTC- 40

Achieving positive and negative speeds with a 0..10V input

Author: Ning Xu, Invertek Drives Ltd

Revision: 2.21 6 September 2006

- ***General:***

Using the bipolar analog input, both positive and negative speed directions can be achieved. This is generally achieved using a bipolar control signal on the analog input (-10V...10V). It is, however, possible to achieve bi-directional speed control with a unidirectional (0..10V) control signal.

This document describes how to configure the drive to achieve bi-directional speed control using a 0..10V control signal.

- ***Drive setup:***

P2-30 Bipolar analog input format

This parameter must be set to "-10V..10V" in order to enable bi-directional motor speed control.

P2-32 Bipolar analog input offset

For a 0..10V input control signal, set this parameter to 50%
For a 0..5V input control signal, set this parameter to 25%

P2-31 Bipolar analog input scaling

For a 0..10V input, set this parameter to 200%
For a 0..5V input, set this parameter to 400%

--- End ---